

### Energy Efficient Refrigeration

Save on costs with the new SunDanzer® 50 liter DC refrigerator. This new 50 liter ultra efficient refrigerator has exceptionally low energy consumption requiring smaller, less expensive power systems and low operating expense.

High quality construction provides excellent reliability and long life. Super-insulated cabinets feature 11cm of polyurethane insulation with powdered-coated galvanized steel exterior and aluminum interior. A zero maintenance, brushless, thermostatically controlled DC compressor operates on 12 or 24 VDC. This chest-style refrigerator is easy to clean using the drain hole at the bottom of the unit.

With thick insulation and a refrigeration system optimized for solar, this new SunDanzer refrigerator will provide outstanding economical and reliable operation.

Low energy consumption is the key that allows SunDanzer refrigerators and freezers to be cost effectively powered from solar, wind, fuel cells or batteries. This technology allows refrigeration in remote locations were it was previously unavailable or prohibitively expensive.

### Applications:

- Remote homes
- Eco-Resorts
- Remote Stores
- Disaster Preparedness
- Beverage Vending
- Churches & Schools
- Villages
- Micro-enterprises
- Cabins
- Medical Clinics
- Markets
- Farms
- Boats and Marine
- Traveling Vendors
- Missionaries

**Container Loading:** 40-ft: 114 units, 20-ft: 54 units



### Features:

- Refrigerators run on a single 45W module in most climates!
- 12 or 24 VDC with low voltage disconnect for battery protection
- Environmentally friendly CFC-free refrigerant (R-134a)
- Rugged scratch resistant galvanized steel exterior
- Easy to clean aluminum interior
- Automatic control with adjustable thermostat

### Specifications:

Voltage: 10-31VDC  
Energy: 114 Watt-hrs/day @ 32C  
9.6 Amp-hrs/day @ 12V, 32C  
Ship Dim: 83H x 71W x 63D cm  
Ext. Dim: 77H x 67W x 59D cm  
Int. Dim: 32H x 45W x 33D cm  
Weight: 29 kg + 5kg packaging

**Typical PV System: 45 Watt panel, 70 Amp-hr battery, 8-Amp Charge Controller**